

# Z-GET06E

This chapter covers the following topics:

- Description
  - Parameters
  - Return Codes
  - Subprograms
  - Example
- 

## Description

Return the meeting version and, if applicable, either the update or cancelation message.

When a new meeting version is created (version 2 or above) and the invitations are sent, an update message is also sent to all attendees.

When the originator cancels the meeting, a cancelation message is sent to all attendees in the following cases:

- when the invitation to the meeting has already been read by one of the attendees (applies only to meeting version 1), or
- when an attendee located at another Con-nect node was invited (applies only to meeting version 1), or
- when the meeting version is 2 or above.

The following only applies to meeting version 1: when none of the attendees has read the invitation, a cancelation message is not sent. In this case, all invitations in the Inbaskets of the attendees are erased. However, when an attendee located at another Con-nect node has also been invited, the invitations are not erased.

This subprogram requires that you specify the ISN of the wanted meeting.

To get the ISN of the current meeting version or of the cancelation notification, invoke Z-GET06B prior to this subprogram.

To get the ISN of a previous meeting version (meeting history), invoke Z-GET06D prior to this subprogram.

## Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Cabinet	A8	R		The cabinet which contains the meeting for which you want information returned.
Password	A8	R		The password of the above cabinet.
Calendar-ISBN	P10		X	The ISBN of the meeting.
Meeting-version	N4		X	Version number of current or previous meeting. 0=cancelation notification is returned.
Message-type	A1		X	0=no message attached to meeting. 1=update message. 2=cancelation message.
Text-array	A37/1:11		X	The text of the message.
Last-text-line	N2		X	The number of the last text line, not considering blank lines at the end of the text.

## Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
04	ISBN was not found
09	ISBN does not point to correct object

## Subprograms

Z-120  
 Z-122  
 Z-123  
 Z-711  
 Z-1200&0

## Example

```
0010 * This subprogram is called from another program which uses Z-GET06B
0020 * and passes the meeting ISN as a parameter
0030 DEFINE DATA
0040 LOCAL
0050 1 RETURN-CODE      (N2)
0060 1 CABINET          (A8)
0070 1 CALENDAR-ISN     (P10)
0080 1 MEETING-VERSION (N4)
0090 1 PASSWORD         (A8)
0100 1 MESSAGE-TYPE     (A1)
0110 1 TEXT-ARRAY       (A37/1:11)
0120 1 LAST-TEXT-LINE  (N2)
0130 1 #I               (N2)
0140 END-DEFINE
0150 *
0160 RESET RETURN-CODE
0170 MOVE 'LS' TO CABINET
0180 MOVE 'LS' TO PASSWORD
0190 MOVE 80715 TO CALENDAR-ISN
0200 *
0210 CALLNAT 'Z-GET06E'
0220 RETURN-CODE
0230 CABINET
0240 PASSWORD
0250 CALENDAR-ISN
0260 MEETING-VERSION
0270 MESSAGE-TYPE
0280 TEXT-ARRAY(*)
0290 LAST-TEXT-LINE
0300 *
0310 IF RETURN-CODE EQ 0
0320 WRITE 'Meeting version' MEETING-VERSION
0330 DECIDE ON FIRST VALUE OF MESSAGE-TYPE
0340 VALUE '0'
0350 IGNORE
0360 VALUE '1'
0370 WRITE 'Meeting update message'
0380 PERFORM PRINT-TEXT
0390 VALUE '2'
0400 WRITE 'Meeting cancelation message'
0410 PERFORM PRINT-TEXT
0420 NONE IGNORE
0430 END-DECIDE
0440 ELSE
0450 WRITE 'Error' RETURN-CODE
0460 END-IF
0470 *
0480 DEFINE SUBROUTINE PRINT-TEXT
0490 IF LAST-TEXT-LINE NE 0
0500 FOR #I 1 LAST-TEXT-LINE
0510 WRITE TEXT-ARRAY(#I)
0520 END-FOR
0530 END-IF
0540 END-SUBROUTINE
0550 *
0560 END
```